

SBA AMPLIFICADOR DE DOS VIAS 037

SBA AMPLIFICADOR DE DOS VIAS 037:

Amplificador de doble vía, tipo line extender, de una salida

| | Forward | Retorno |
|----------------------|------------------------|----------|
| Bandwidth | xx-862 MHz 1000 MHz | 5-xx MHz |
| Minimum full gain | 30 dB | 20 dB |
| Nominal Input Level | 12 dBmV | 12 dBmV |
| Noise Figure | ≤8 dB | ≤9 dB |
| Nominal Output Level | 42 dBmV | 32 dBmV |
| CTB | 62 dB | |
| CSO | 63 dB | |
| Return loss | >16 dB | >14 dB |
| Gain adjust range | 0-20 dB | 0-20 dB |
| Eq. adjustable range | 0-18 dB | 0-18 dB |
| Manual level control | 0-8 dB | |
| Test port | -20 dB | -20dB |
| Supply voltage | VAC 60/90 | |
| Power consumption | 30 Watts | |

