

SBA NODO HFC 034

SBA NODO HFC 034: Receptor óptico para redes HFC. Excelente sistema AGC que mantiene los niveles de salida. Puede ser configurado con dos o cuatro salidas.

FORWARD PATH	
Optical wavelenght	1310, 1550 nm
Receiving optical power	-7 to +2 dBm
Optical AGC control range	-7 to +2 dB
Return loss	>16 dB
Bandwidth	xx-862(1000) MHz
Output Level	50 dBmV
C/N	>51 dB
Power consumption	25 wats
RETURN PATH	
Optical wavelenght	1310 +/- 30 nm 1550 +/- 30 nm
Type of Laser	IFP with isolator
Output optical power	-0.4 to +2 dBm
RF Bandwidth	5-xx MHz
RF input level	15 to 25 dBmV



SBA

SOLUCIONES DE BANDA ANCHA